SafeCom printing for Ubuntu

SafeCom printing for Ubuntu, WiFi printing

Step-by-step guide

1. Click on Show Applications



2. Navigate to Settings.



3. Go to Devices.



4. Click on Printers.



5. Scroll down and click on Additional Printers



6. Click on ADD

C Devices	Printers	Q Add
Displays	Model Hewlett-Packard HP LaserJet 400 M401	tdn
00 Keyboard		
🕼 Mouse & Touchpad	HP_LaserJet_400_M401dn_152 Ready	No Active Jobs
Printers	Printers - Ioralhost	
Removable Media	View Help	
站 Wacom Tablet	🙅 Add 👻 😋 🛛 Filter: 🔍	
de Color		NO ACTIVE JODS
	HP_LaserJet_400_M401dn_ HP_LaserJet_400_M401d 151829 1528F5	dn_
		No Active Jobs
	HP_LaserJet_400_M401dn_ HP_LaserJet_600_M603 63SA46_ DFDC_	.07
	Connected to localhost	
	Ready	No Active Jobs
	Model KONICA MINOLTA KONICA MINOLTA biz	zhub C3350

7. Select Network printer and then Windows printer via SAMBA



8. Enter SMB Printer path (Depending on what printer you would like to add, see list below)

- a. Under Authentication select Set authentication details now.
- **b.** Password will be your **student password**.
- c. For username use stb\your student number.
- d. When done click on FORWARD.

<							
9	Displays	Model 1	Hewlett-Packard HP Laser Jet 4007	4401da			
8	Keyboard						
÷	Mouse & Touchp	ad 📫	HP_LaserJet_400_M401dn_ Bready	1528F5_	No Active Job	5 0	
	Printers		New Printer		000		
	Removable Mer	Select Device					
24	Wacom Tablet Color	Devices KONICA MINOLTA C3850 (BHC) KONICA MINOLTA C38515eries HP Laser Jet P2055cln (146.232	SMB Printer smb:// tbsc05.stb.sun.ac.za/ smb:///weekgroup/jserver[.port	STB_PRINT_Q01]/printer	Browse	8 0	
	HP LI HP LI KONI HP LI HP LI HP LI HP LI	HP LaserJet 2420 (146, 232, 75, HP LaserJet 400 M401dn (146, HP LaserJet 600 M603 (146, 23, KONICA MINOLTA C3850 (8HC) HP LaserJet 400 M401dn (NPI1 HP LaserJet 400 M401dn (NPI HP LaserJet M272 nr MFP (NP Find Network Printer	Prompt user if authentication is required Set authentication details now Password: Username: yourusername verify_			6 0	
		Windows Prinker via SAMBA LPD/LPR Host or Printer AppSocket/HP JetDirect Internet Printing Protocol (ipp Internet Printing Protocol (ipt Internet Printing Protocol (ipt)	 Connection Windows Princer via SAMBA 				
	_			Cancel	Forward	Settings.	

9. Staff -> \\stbsc01.stb.sun.ac.za\STB_PRINT_Q01

FHARGA -> \\stbsc02.stb.sun.ac.za\STB_PRINT_Q01 NARGA -> \\stbsc03.stb.sun.ac.za\STB_PRINT_Q01 HUMARGA -> \\stbsc04.stb.sun.ac.za\STB_PRINT_Q01 FIRGA, Library -> \\stbsc05.stb.sun.ac.za\STB_PRINT_Q01

10. Select printer from database, choose HP and click FORWARD



11. Choose driver model LASER JET 4000 and DRIVER HP LASER JET 4000-CUPS+Gutenprint v5.2.13

Moure 8 Touchos	HP La:	serJet 400 M401dn 1528F5	1 (20)			
mouse a roucipa	Povda	New Printer				
Printers						
Removable Med	d Choose Driver					
	Models	Drivers				
Wacom Tablet	LaserJet 3330 Multifunction	HP LaserJet 4000 Series Postscript [en] (rect	0			
Color	Laser Jet 3380	HP LaserJet 4000 Series pcl3, hpcups 3.17.10	(<u>*</u>)			
120.00	LaserJet 3390	HP Laser let 4000 Ecomatic (Postscript len)				
	Laser Jet 3392	HP LaserJet 4000 - CUPS+Gutenprint vS.2.13				
	Laser let 4000	HP Laser let 4000 Foomatic/rj/ggray [en]				
	Laser Jet 4000se	HP Laser Jet 4000 Series holis p.cl3, 3, 17, 10 fe				
	LaserJet 4000t		0			
	LaserJet 4000th					
	LaserJet 4050					
	LaserJet 4050n					
	LaserJet 4050se					
	aserJet 4050t		0			
	LaserJet 4050th		- 20			
	LaserJec 4100					
	Lase Jet 4100 MPP					
	Keyboard Mouse & Touchpa Printers Removable Med Wacom Tablet Color	Keyboard Mouse & Touchpad Printers Removable Med Wacom Tablet Color Laser Jet 3330 Laser Jet 3390 Laser Jet 3390 Laser Jet 3390 Laser Jet 3390 Laser Jet 3000t Laser Jet 4000t	Keyboard Mouse 8. Touchpad Printers Removable Me Wacom Tablet Color Models Laser Jet 3330 Multifunction Laser Jet 3330 Multifunction Laser Jet 3390 Laser Jet 3390 HP Laser Jet 4000 Series postscript [en] (rect HP Laser Jet 4000 Series postscript [en] Laser Jet 3390 HP Laser Jet 4000 Series postscript [en] Laser Jet 3390 HP Laser Jet 4000 Series postscript [en] Laser Jet 300 HP Laser Jet 4000 Series postscript [en] Laser Jet 300 HP Laser Jet 4000 Series postscript [en] Laser Jet 4000 Series postscript [en] Laser Jet 4000 Series postscript [en] Laser Jet 4000 HP Laser Jet 4000 Series postscript [en] Laser Jet 4000 Series postscript			

- 12. Choose name of the printer and description and click apply
- 13. Print test page.

1. Please DO NOT MAKE any other changes here, only change account name to your student number/alias.

Related articles

0

- SafeCom Printer setup for MacOS Sonoma
- FAQs Register & Connecting to Eduroam
- SafeCom
- ICT Charges (EUS)
- Connectivity